

BANMORE ELECTRICALS PVT LTD

CRGO CORE LOSSES OF ALL GRADES (w/kg 50 hz) -- Approx Figurers and Losses Graph vary from Mill to Mill

Flux Density (Tesla)	23HP70 d	23HP75 d	23HP80 d	23HP85 d	23HP90 d	23HP95 d	27HP90 d	27hp95 d	23HP100	27HP100	30HP105	23CG110 27HP110	27CG120 M4	30CG130 M5
1.3	0.38	0.40	0.42	0.45	0.48	0.51	0.51	0.54	0.53	0.57	0.57	0.49	0.54	0.64
1.35	0.42	0.44	0.46	0.49	0.52	0.55	0.55	0.58	0.57	0.6	0.62	0.53	0.58	0.68
1.4	0.46	0.48	0.50	0.53	0.56	0.59	0.59	0.62	0.61	0.66	0.65	0.58	0.63	0.73
1.45	0.48	0.50	0.53	0.57	0.6	0.63	0.63	0.66	0.66	0.7	0.7	0.64	0.69	0.79
1.46	0.50	0.515	0.54	0.58	0.61	0.64	0.64	0.67	0.67	0.71	0.71	0.65	0.7	0.8
1.48	0.51	0.53	0.555	0.6	0.63	0.66	0.66	0.69	0.66	0.73	0.74	0.67	0.72	0.82
1.5	0.53	0.55	0.57	0.61	0.64	0.67	0.67	0.70	0.70	0.74	0.76	0.7	0.75	0.85
1.52	0.545	0.565	0.59	0.63	0.66	0.69	0.69	0.72	0.72	0.76	0.78	0.72	0.77	0.87
1.54	0.56	0.58	0.61	0.65	0.68	0.71	0.71	0.74	0.74	0.79	0.8	0.75	0.8	0.9
1.56	0.58	0.60	0.63	0.67	0.7	0.73	0.73	0.76	0.76	0.81	0.83	0.78	0.83	0.93
1.58	0.595	0.625	0.65	0.69	0.72	0.75	0.75	0.78	0.78	0.83	0.85	0.81	0.86	0.96
1.6	0.615	0.64	0.67	0.71	0.74	0.78	0.77	0.8	0.8	0.85	0.87	0.85	0.95	1.07
1.62	0.63	0.65	0.70	0.73	0.76	0.8	0.79	0.82	0.83	0.89	0.9	0.89	0.99	1.11
1.64	0.65	0.67	0.72	0.75	0.78	0.82	0.81	0.84	0.85	0.91	0.93	0.93	1.03	1.15
1.66	0.67	0.695	0.74	0.78	0.81	0.86	0.84	0.87	0.88	0.94	0.96	0.98	1.06	1.18
1.68	0.68	0.73	0.76	0.81	0.84	0.89	0.87	0.9	0.93	0.96	1	1.03	1.11	1.23
1.7	0.70	0.74	0.79	0.83	0.87	0.92	0.9	0.93	0.95	1	1.05	1.09	1.14	1.26
1.72	0.74	0.77	0.83	0.86	0.9	0.93	0.93	0.96	0.98	1.02	1.07	1.15	1.2	1.3